

K2 LITE

USER MANUAL

RECHARGEABLE KEYCHAIN LIGHT
USB-C CHARGING PORT
1000 LUMENS MAXIMUM OUTPUT

Specification

- Main light: utilized 2 high performance LEDs to deliver the max output of 1000 lumens
- Colorful light: composed of three forms-static, dynamic and flowing, can make about 20 different lighting effects
- USB Type-C charging, fully charged in 1 hour
- Aerospace Aluminum body with a cute owl appearance
- Modes(main light): High-Medium-Low-Eco and Strobe
- Multi-functional two-way clip for different purpose
- Max run time up to 20 hours
- Power indication function
- 280mAh built-in battery
- Small and light weight: 64(L)*32(W)*12(H)mm, 44g(aluminum)
- Accessories Included: 1*charging cable, 1* keychain, 1* clip

K2 LITE Data

FL1 STANDARD	HIGH	MEDIUM	LOW	ECO	STROBE
OUTPUT	1,000 Lumens	150 Lumens	30 Lumens	2 Lumens	1,000 Lumens
RUNTIME	15min	45min	3h	20h	/
INTENSITY	1,805cd				
DISTANCE	100m(Max)				
WATERPROOF	IP5(without waterproof)				
IMPACT RESISTANCE	1m				

Note: all datas above were generated in Fitorch lab. Differences may happen basing on usage and conditions.

Operation

- **On/Off**:
  Press the side switch to turn on the light, and then press the side switch again to turn off the light.
- **Mode change:(white)**
  When power on, click the side switch to cycle through High-Medium-Low-Eco-High-Medium-Low.
- **Colorful Mode:**
  when the light is on strobe, double click the switch to enter the Red&Blue flash, and then click the switch 3 times to enter colorful mode. Click the side switch to change the colorful light effect.
  When the light is off, click the side switch 3 times to enter colorful mode directly, and then click the side switch to change the colorful light effect.
- **Strobe Function:**
  Double click the side switch to activate Strobe.
- **Power Indication:**
  When open the light, the power indicator below the side switch will indicate the current power by displaying green or red. Green light:75%-100%; Green flash: 50%-75%; Red light: 25%-50%; Red flash: <25%.
- **Charging**
  Switch off the light and remove the USB cap to reveal the USB Type-C charging port, and then connect the charging port and the power source by charging cable. The indicator will be red during charging, and it will change to green after charging.

Usage and Maintenance

- Disassembling the sealed head will damage the lights and void the warranty.
- High quality batteries are recommended.
- O-ring will be wear after a Long-term use, change it In included spare one to maintain watertight seal.
- Unload the batteries if assure the light won't use a bit of long time, then better put It into Inner box(Built-in battery excluded).
- Store and keep the light off fire, statics, steaming and humidity surroundings.
- Clean the body with soft fabric clothing then lubricate In silicon grease per half a year.
- Periodic cleaning of batteries contacts to improve the flashlight performance as dirty contacts cause the lamp flicking, shine intermittently or even fail to illuminate for below factors(Built-in battery excluded).
  A: Battery needs replacing (choose the battery which mentions on this manual)
  B: PCB, Spring or other contacts is dirty (clean the contacts In cotton swab In soaked rubbing alcohol)

WARNING!

- Looking at the light for a long time will harm your eyes. Don't shine the light directly into anyone's eyes.
- The light will accumulate a lot of heat when used for extended periods, resulting in a high temperature of the light housing. Pay attention to safe use to avoid scalding.
- Do not shine the light to an object at close range to avoid burning the object or causing danger due to high temperature.

Warranty

- 15 days replacement: Fitorch will replace indentical or equal products with documented manufacturing defects within 15 days of purchase.
- 2-year free repair: This light is non-detachable and enjoy the service of 2 year free repair of purchase if problems happen in normal use.
  Rechargeable battery enjoys 1-year warranty.

Facebook Website

ShenZhen Fitorch Electronics Technology Co., Ltd
Office Address: 2F, Building 2, 3rd Industrial Zone, Longhua St, Longhua District, ShenZhen City, 518109, China
Tel: +86-755-2101-3606
Web: www.fitorchworld.com
E-mail: Info@fitorchworld.com

CE RoHS